

Синтезаторы частот с двумя номиналами напряжения питания

Модель	Рабочий диапазон частот, MHz	Шаг перестройки (kHz)	Минимальный уровень вых. мощности, dBm	Уровень фазовых шумов на отстройке, dBc/Hz	
				@10 kHz	@100 kHz
FSW511-50	50 - 115	500	+6	-112	-127
FSW1125-10	110 - 250	100	+5	-104	-132
FSW1125-50	110 - 250	500	+5	-105	-130
FSW1545-50	150 - 450	500	0	-102	-120
FSW1857-100	180 - 570	1000	+3	-98	-120
FSW2476-10	240 - 760	100	0	-98	-124
FSW2476-50	240 - 760	500	0	-93	-120
FSW40110-50	400 - 1100	500	0	-95	-122
FSW50120-50	500 - 1200	500	0	-97	-118
FSW60135-50	600 - 1350	500	+1	-92	-118
FSW60170-50	600 - 1700	500	0	-90	-117
FSW80150-10	800 - 1500	100	+5	-92	-118
FSW80210-50	800 - 2100	500	+5	-90	-113
FSW85150-50	850 - 1500	500	+4	-93	-120
FSH9496-20	940 - 970	200	+5	-109	-134

FSW100230-50	1000 - 2300	500	+4	-92	-115
FSH127171-50	1270 - 1710	500	+1	-95	-122
FSW150320-10	1500 - 3200	100	+3	-79	-108
FSW150320-50	1500 - 3200	500	+1	-86	-112
FSW170280-50	1700 - 2800	500	+3	-85	-112
FSW190410-50	1900 - 4100	500	-3	-82	-107
FSW190410-100	1900 - 4100	1000	0	-85	-110
FSW200400-100	2000 - 4000	1000	0	-85	-110
FSW216265-50	2160 - 2650	500	+2	-92	-122
FSH250300-100	2500 - 3000	1000	+4	-92	-122
FSH250300-1M	2500 - 3000	10000	+8	-98	-122
FSW300600-100	3000 - 6000	1000	-2	-80	-100
FSH310410-1M	3100 - 4100	10000	+5	-90	-96



The Signal Source Noise Control & Signal Processing Experts.