

## RLAC001180A Advanced

## 0.1 ~ 18.0 GHz Low Noise Amplifier 🕮

### **Key Features:**


Broad Frequency Range: High Gain: Low NF: High P1dB: Single DC Supply: Connectors: 0.1 ~ 18.0 GHz 28 dB 3.0 dB (typical), 5.0 dB (max) 15 dBm (typ) +15V @ 150mA SMA Female

Photo not available

## Electrical Specifications<sup>1</sup>: (at +25°C)

| Testing Item               | Symbol | Test Conditions | Min | Nom    | Max  | Unit |
|----------------------------|--------|-----------------|-----|--------|------|------|
| Frequency Range            | BW     |                 | 0.1 |        | 18.0 | GHz  |
| Gain                       | S21    | 0.1 ~ 18.0 GHz  |     | 28     |      | dB   |
| Gain Flatness              | ΔG     | 0.1 ~ 18.0 GHz  |     | +/-1.5 |      | dB   |
| Noise Figure               | NF     | 0.1 ~ 18.0 GHz  |     | 3.0    | 5.0  | dB   |
| Reverse Isolation          | S12    | 0.1 ~ 18.0 GHz  |     | TBD    |      | dB   |
| VSWR                       |        | 0.1 ~ 18.0 GHz  |     |        | 2:1  |      |
| Power at 1dB Gain Compress | P1dB   | 0.1 ~ 18.0 GHz  |     | 15     |      | dBm  |
| DC Voltage                 | Vd     |                 |     | +15    |      | Volt |
| DC Current                 | ld     |                 |     | 150    |      | mA   |
| Operating Temperature      |        |                 | -40 |        | +70  | 0 C  |
| Impedance                  |        | 0.1 ~ 18.0 GHz  |     | 50     |      | ohm  |

## Outline Drawing (not scaled)



Available exclusively from Richardson RFPD - 800-737-6937 (U.S. & Canada) - 630-208-2700 (International) Or visit www.richardsonrfpd.com. See important product notice on last page of this document.

| Internal Richardson Document # | Origination Date: | Rev: 2A          | Dogo | 1/0 |
|--------------------------------|-------------------|------------------|------|-----|
|                                | March 2008        | Date: March 2011 | Page | 1/2 |
|                                |                   |                  |      |     |

<sup>&</sup>lt;sup>1</sup> Specifications are subject to change without notice.



# RLAC001180A Advanced

### **Ordering Information**

Part Number RLAC001180A

Richardson RFPD, Inc. 40W267 Keslinger Road P.O. Box 307 LaFox, IL 60147 Telephone: (800) 737-6937 (630) 208-2700 Fax: (630) 208-2662 Internet: www.richardsonrfpd.com

#### **IMPORTANT NOTICE**

RICHARDSON RFPD, INC. AND ITS AFFILIATES RESERVE THE RIGHT TO MAKE CHANGES TO THE PRODUCT(S) OR INFORMATION CONTAINED HEREIN WITHOUT NOTICE. RICHARDSON RFPD, INC. ASSUMES NO RESPONSIBILITY FOR ANY ERRORS WHICH MAY APPEAR IN THIS DOCUMENT.

WARRANTY INFORMATION APPLICABLE TO THE PRODUCT IDENTIFIED HEREIN IS AVAILABLE UPON REQUEST. NOTHING CONTAINED HEREIN SHALL CONSTITUTE A WARRANTY, REPRESENTATION OR GUARANTEE OF ANY KIND. RICHARDSON RFPD, INC. EXPRESSLY DISCLAIMS ALL OTHER WARRANTIES, EXPRESS AND/OR IMPLIED INCLUDING BUT NOT LIMITED TO WARRANTIES OF MERCHANTABILITY, AND OF FITNESS FOR A PARTICULAR PURPOSE, USE OR APPLICATION.

NO PART OF THIS DOCUMENT MAY BE COPIED OR REPRODUCED IN ANY FORM OR BY ANY MEANS WITHOUT THE PRIOR WRITTEN CONSENT OF RICHARDSON RFPD, INC.

#### WARNING

RICHARDSON RFPD, INC. PRODUCTS ARE NOT INTENDED FOR USE IN LIFE SUPPORT APPLIANCES, DEVICES OR SYSTEMS. USE OF A RICHARDSON RFPD, INC. PRODUCT IN ANY SUCH APPLICATION WITHOUT WRITTEN CONSENT IS PROHIBITED.

Available exclusively from Richardson RFPD - 800-737-6937 (U.S. & Canada) - 630-208-2700 (International)

| Of visit www.inchardsompd.com. See important product notice on last page of this document. |                   |                  |          |  |  |
|--|-------------------|------------------|----------|--|--|
| Internal Richardson Document #   | Origination Date: | Rev: 2A          | Page 2/2 |  |  |
|  | March 2008        | Date: March 2011 | Faye 2/2 |  |  |