

**Широкополосные квадратурные мосты**

Модель	Частотный диапазон, (MHz)	Вносимые потери, (dB) [Ном./Макс.]	Разбаланс амплитуды, (dB) [Ном./Макс.]	Разбаланс фазы (град.) [Ном./Макс.]	Изоляция (dB) [Ном./Мин.]	Макс. уровень вх. мощности (W)
DQS-3-32	3 - 32	1.0/1.5	0.9/1.2	2.0/3.0	25/20	1
DQP-2-16	2 - 32	0.8/1.0	0.1/1.0	3.0/5.0	23/20	1
DQS-5-50	5 - 50	1.0/1.5	0.9/1.2	2.0/3.0	25/20	1
DQS-10-50	10 - 50	0.8/1.0	0.5/0.9	1.5/3.0	30/20	1
DQS-10-100	10 - 100	1.0/1.5	0.9/1.2	2.0/3.0	25/20	1
DQS-15-150	15 - 150	1.2/1.7	0.9/1.2	2.5/4.0	25/17	1
DQS-20-100	20 - 100	0.6/1.0	0.5/0.8	1.5/3.0	27/20	1
DQS-20-200	20 - 200	1.3/1.8	0.9/1.2	2.5/4.0	25/17	1
DQS-25-250	25 - 250	1.5/2.0	0.9/1.2	2.5/4.0	25/17	1
DQS-A13	30 - 90	0.3/0.6	1.1/1.7	2.0/4.0	23/20	150
DQS-30-90	30 - 90	0.3/0.6	0.8/1.2	1.0/3.0	23/18	25
DQS-3-11-10	30 - 110	0.5/0.8	0.6/0.9	1.0/3.0	30/20	10
DQS-30-150	30 - 150	0.8/1.0	0.5/0.9	1.5/3.0	30/20	1
DQS-30-300	30 - 300	1.5/2.0	1.0/1.4	3.0/5.0	25/16	1
DQS-30-450	30 - 450	1.2/1.7	1.0/1.5	4.0/6.0	23/18	5
DQS-40-200	40 - 200	0.9/1.0	0.5/1.0	2.0/4.0	30/18	1
DQS-40-400	40 - 400	1.7/2.2	1.0/1.5	3.0/5.0	25/16	1
DQS-45-450	45 - 450	1.7/2.2	1.0/1.4	3.0/5.0	25/15	1
DQS-50-250	50 - 250	0.9/1.0	0.5/1.0	2.0/4.0	30/18	1

DQS-50-500	50 - 500	1.7/2.2	1.0/1.5	3.0/5.0	23/15	1
DQP-50-500	50 - 500	1.7/2.2	1.0/1.5	3.0/5.0	23/15	1
DQK-50-500S	50 - 500	1.7/2.2	1.0/1.5	3.0/5.0	23/15	1
DQS-90-450	90 - 450	1.2/1.5	0.7/1.0	3.0/5.0	22/16	1
DQP-90-450	90 - 450	1.2/1.5	0.7/1.0	3.0/5.0	22/16	1
DQS-100-500	100 - 500	1.2/1.5	0.8/1.25	3.0/5.0	25/16	1
DQP-100-500	100 - 500	1.2/1.5	0.8/1.25	3.0/5.0	25/16	1
DQK-100-500	100 - 500	1.2/1.5	0.8/1.25	3.0/5.0	25/16	1
DQS-100-1000	100 - 1000	1.7/2.3	1.2/1.8	6.0/10	25/16	1
DQS-A16	118 - 174	0.3/0.6	0.4/1.0	1.0/3.0	23/18	25
SMJ-C6	20 - 1200	1/1.5	0.6/1.0	2.0/4.0	19/15	25
SMJ-CA13	500 - 1500	1.5/2.5	0.5/1.0	5.0/8.0	20/15	1
SJL-115	200 - 1200	1/1.5	0.6/1.0	2.0/4.0	19/15	25
MSQ80300	800 - 3000	0.2/0.4	0.5/0.8	2.0/5.0	20/18	40
DQK-1723S	1700 - 2300	0.0/0.3	0.0/0.35	2.0/3.0	23/18	50
MSQ100800	1000 - 8000	0.8/1.6	1.0/1.6	1.0/4.0	22/20	40
DQK-2-125B	2 - 250	1.8/2.0	1.1/1.3	4.0/6.0	18/15	1
DQK-2-16B	3 - 32	0.8/1.0	0.9/1.0	1.0/3.0	23/20	1
DQK-3-32S	3 - 32	1.0/1.5	0.9/1.2	2.0/3.0	25/20	1
DQK-5-50S	5 - 50	1.0/1.5	0.9/1.2	2.0/3.0	25/20	1
DQK-10-50S	10 - 50	0.8/1.0	0.5/0.9	1.5/3.0	30/20	1
DQK-10-100S	10 - 100	1.0/1.5	0.9/1.2	2.0/3.0	25/20	1

DQK-20-100S	20 -100	0.6/1.0	0.5/0.8	1.5/3.0	27/20	1
DQK-20-200S	20 - 200	1.3/1.8	0.9/1.2	2.5/4.0	25/17	1
DQK-25-250S	25 - 250	1.5/2.0	0.9/1.2	2.5/4.0	25/17	1
DQK-30-150S	30 - 150	0.8/1.0	0.5/0.9	1.5/3.0	30/20	1
DQK-30-300S	30 - 300	1.5/2.0	1.0/1.4	3.0/5.0	25/16	1
DQK-45-450S	45 - 450	1.7/2.2	1.0/1.4	3.0/5.0	25/15	1
DQK-50-250S	50 - 250	0.9/1.0	0.5/1.0	2.0/4.0	30/18	1
DQK-90-450S	90 - 450	1.2/1.5	0.7/1.0	3.0/5.0	22/16	1
DQK-100-500S	100 - 500	1.2/1.5	0.8/1.25	3.0/5.0	25/16	1
DQK-100-1000S	100 - 1000	1.7/2.3	1.2/1.8	6.0/10	25/16	1
DQK80300	800 - 3000	0.2/0.4	0.5/0.8	2.0/5.0	20/18	40
DQK100800	1000 - 8000	0.8/1.6	1.0/1.6	1.0/4.0	22/20	40



*The Signal Source Noise Control & Signal Processing Experts.*