

Полосовые фильтры

| Модель | Цетральная частота, (MHz) | Потери в полосе (макс.), dB | Полоса пропускания, (MHz) | Полоса пропускания по уровню 35dB, (MHz) |
|----------|---------------------------|-----------------------------|---------------------------|--|
| FNS-10.7 | 10.7 | 1.7 | 10.2 - 11.2 | 5.1 - 22.5 |
| FNS-21.4 | 21.4 | 1.7 | 20.3 - 22.5 | 10.2 - 45.0 |
| FNS-30 | 30.0 | 1.7 | 28.5 - 31.5 | 14.3 - 63.0 |
| FNS-45 | 45 | 1.7 | 42.8 - 47.3 | 21.3 - 94.5 |
| FNS-50 | 50 | 1.7 | 47.5 - 52.5 | 23.8 - 105 |
| FNS-60 | 60 | 1.7 | 57.0 - 63.0 | 28.4 - 126 |
| FNS-70 | 70.0 | 1.7 | 66.5 - 73.5 | 33.3 - 147 |
| FNS-100 | 100 | 2.7 | 95.0 - 105 | 47.5 - 210 |
| FNS-120 | 120 | 2.7 | 114 - 126 | 57.0 - 252 |
| FNS-140 | 140 | 2.7 | 133 - 147 | 66.5 - 294 |
| FNS-160 | 160 | 2.7 | 152 - 168 | 76.0 - 336 |
| FNS-180 | 180 | 2.7 | 171 - 189 | 85.5 - 378 |
| FNS-200 | 200 | 2.7 | 190 - 210 | 95 - 420 |
| FNS-250 | 250 | 3.0 | 238 - 262.5 | 119 - 525 |
| FNS-300 | 300 | 3.0 | 285.7 - 315 | 142.8 - 630 |
| FNS-350 | 350 | 3.0 | 333.3 - 367.5 | 166.7 - 735 |

| | | | | |
|---------|-----|-----|---------------|--------------|
| FNS-400 | 400 | 3.0 | 380.9 - 420 | 190.5 - 840 |
| FNS-450 | 450 | 3.0 | 428.6 - 472.5 | 214.3 - 945 |
| FNS-500 | 500 | 3.0 | 476.2 - 525 | 238.1 - 1050 |



The Signal Source Noise Control & Signal Processing Experts.