

## Advanced

## 0.45 ~ 3.8 GHz Low Noise Amplifier 🕮

## **Key Features:**

Broad Frequency Range: 0.45 ~ 3.8 GHz

High Gain: 44 dB

Low NF: 1.20 dB (typical) High OIP3: 40 dBm (typical)

Single DC Supply: +11V to +15V @ 230 mA


Connectors: SMA Female

### Photo not available

## Electrical Specifications: (at +25°C)

Testing Item	Symbol	Test Conditions	Min	Nom	Max	Unit
Frequency Range	BW		0.45		3.8	GHz
Gain	S21	0.45 ~ 3.8 GHz	43	44	46.5	dB
Gain Flatness		0.45 ~ 3.8 GHz, per every 20MHz		+/- 1.0	+/-1.3	dB
Gain Vs. Temperature		0.45 ~ 3.8 GHz			0.02	dB/°C
Noise Figure	NF	0.45 ~ 3.8 GHz		1.2	1.5	dB
VSWR		0.45 ~ 3.8 GHz		1.5:1	1.8:1	
Power at 1dB Gain Compress	P1dB	0.45 ~ 3.8 GHz	22	24		dBm
Third Order Intercept Point	OIP3	0.45 ~ 3.8 GHz	36	40		dBm
Second Order Intercept Point	OIP2	0.45 ~ 3.8 GHz	45	47		dBm
DC Voltage			+11		+15	Volt
DC Current				230		mA
Operating Temperature			-40		+85	°C
Impedance				50		ohm

#### Outline Drawing (not scaled)



Available exclusively from Richardson RFPD - 800-737-6937 (U.S. & Canada) - 630-208-2700 (International) Or visit <a href="https://www.richardsonrfpd.com">www.richardsonrfpd.com</a>. See important product notice on last page of this document.

Internal Richardson Document #	Origination Date:	Rev: 5A	Page 1/2
	March 2008	Date: September 2013	Page 1/2

## RLAC0438A



# Advanced

### **Ordering Information**

|--|

#### Richardson RFPD, Inc.

40W267 Keslinger Road P.O. Box 307 LaFox. IL 60147

Telephone: (800) 737-6937

(630) 208-2700

Fax: (630) 208-2662 Internet: www.richardsonrfpd.com

#### **IMPORTANT NOTICE**

RICHARDSON RFPD, INC. AND ITS AFFILIATES RESERVE THE RIGHT TO MAKE CHANGES TO THE PRODUCT(S) OR INFORMATION CONTAINED HEREIN WITHOUT NOTICE. RICHARDSON RFPD, INC. ASSUMES NO RESPONSIBILITY FOR ANY ERRORS WHICH MAY APPEAR IN THIS DOCUMENT.

WARRANTY INFORMATION APPLICABLE TO THE PRODUCT IDENTIFIED HEREIN IS AVAILABLE UPON REQUEST. NOTHING CONTAINED HEREIN SHALL CONSTITUTE A WARRANTY, REPRESENTATION OR GUARANTEE OF ANY KIND. RICHARDSON RFPD, INC. EXPRESSLY DISCLAIMS ALL OTHER WARRANTIES, EXPRESS AND/OR IMPLIED INCLUDING BUT NOT LIMITED TO WARRANTIES OF MERCHANTABILITY, AND OF FITNESS FOR A PARTICULAR PURPOSE, USE OR APPLICATION.

NO PART OF THIS DOCUMENT MAY BE COPIED OR REPRODUCED IN ANY FORM OR BY ANY MEANS WITHOUT THE PRIOR WRITTEN CONSENT OF RICHARDSON REPD. INC.

#### **WARNING**

RICHARDSON RFPD, INC. PRODUCTS ARE NOT INTENDED FOR USE IN LIFE SUPPORT APPLIANCES, DEVICES OR SYSTEMS. USE OF A RICHARDSON RFPD, INC. PRODUCT IN ANY SUCH APPLICATION WITHOUT WRITTEN CONSENT IS PROHIBITED.

Available exclusively from Richardson RFPD - 800-737-6937 (U.S. & Canada) - 630-208-2700 (International) Or visit <a href="www.richardsonrfpd.com">www.richardsonrfpd.com</a>. See important product notice on last page of this document.